



Technical Data  
Surelight EL Inverters  
List 1



Model	Length m	Input Voltage VDC	Output Voltage VAC	Modes	Frequency Hz	Batteries	Operating temperature °C
<b>KH1.5</b>	0.1 - 1.0	6	120	Flash/Continuous	2500	LR14 x 4	- 20 to 65
<b>KH3</b>	0.4 - 1.0	3	110	Flash/Continuous	2000	AA x 2	- 20 to 55
<b>KH4</b>	0.5 - 2.5	3	105	Flash/Continuous	2000	AA x 2	- 20 to 55
<b>KH5</b>	0.5 -10.0	6	100	Flash/Continuous	2000	AAA x 4	- 20 to 55
<b>KD5</b>	0.5 – 14.0	6	120	Flash/Continuous	2000	AAA x 4	- 20 to 55
<b>L5</b>	1.0 – 6.0	12	115	Continuous	2500	12V	- 20 to 55
<b>L10</b>	0.5 -15.0	12	100	Flash/Continuous	1800	12V	- 20 to 55
<b>L30</b>	15.0 – 30.0	12	90	Flash/Continuous	1800	12V	- 20 to 55
<b>KD15</b>	2.0 – 20.0	12	90	Flash/Continuous	1200	12V	- 20 to 55
<b>KD30</b>	5.0 –20.0	12	90	Flash/Continuous	1200	12V	- 20 to 55
<b>KD30B</b>	5.0 – 30.0	12	90	Flash Continuous	700	12V	-20 to 55
<b>KH30</b>	15 – 40	240 (PSU)/12	100	Continuous	2000	NA	- 20 to 55
<b>KH40</b>	20.0 – 40	12	110	Continuous	1200	12V	- 20 to 55
<b>KH100</b>	60.0 – 100.0	12	120	Continous	1200	12V	- 20 to 55
<b>KH200D</b>	75.0 – 230.0	240 (PSU)/24	120	Continuous/Manual Fade	1200	NA	- 20 to 55
<b>KH400</b>	250.0 – 600.0	240 (PSU)/12	120	Continous	1200	NA	- 20 to 55

All figures shown are Typical & are subject to change  
**Please ask if this list does not show the unit you require.**

Olmecc Advanced Materials Ltd/Surelight  
[www.surelight.com](http://www.surelight.com); [info@surelight.com](mailto:info@surelight.com)  
[www.olmec.co.uk](http://www.olmec.co.uk); [info@olmec.co.uk](mailto:info@olmec.co.uk)

12 Terminus Rd, Millhouses, Sheffield, S7 2LH. United Kingdom  
Tel: +44 (0) 114 236 1606 - Fax: +44 (0) 114 262 1202  
GB Reg No. 247 6257 - VAT No. 570 6797 06



Model	Length m	Input Voltage VDC	No. Outputs	Output Voltage VAC	Modes	Frequency Hz	Batteries	Operating temperature °C (Degrees)
IF4	0.5 - 2	3	1	100	Flash/Continuous	4000	AA x 2	- 20 to 55
CD2K***	0.5-7.0	12	1	110	Continuous	2000	12V	- 20 to 55
KHVOX	1 - 6	12 - 15	1	100	Continuous	800	12V	- 20 to 55
L9375/1	0.1 - 2	9	1	120	Flash/Continuous	1500	AAA x 4	- 20 to 55
L9375/2	0.1 - 2	9	2	120	Alternate Flash	1500	AAA x 4	- 20 to 55
L9361/3	0.1 - 2	6	3	120	Flash/Sequence	1500	AAA x 4	- 20 to 55
L9372/1	1 - 6	6	1	120	Flash/Continuous	1500	AAA x 4	- 20 to 55
L9418/1*	1 - 10	12	1	100	Flash/Continuous	1200	AAA x 4	- 20 to 55
L9424/2	10 - 100	12	2	120	Alternate Fade	1200	12V	- 20 to 55
L9397/4*	10 - 100	12	4	140	Fade	1200	12V	- 20 to 55
L9396/4#	2 - 15	12	4	120	Sequencing	1400	12V	- 20 to 55
L9396/8	2 - 15	12	8	120	Sequencing	1400	12V	- 20 to 55
L9423/4*	40 - 100	12	4	100	Sequencing	1200	12V	- 20 to 55
L9423/8*	40 - 100	12	8	100	Sequencing	1200	12V	- 20 to 55
L9397/1	5 - 30	12	1	120	Flash/Continuous	1800	12V	- 20 to 55
WIZZ**	15/150	9/12	10	120	Continous/Flash /Sequence	2000	PP3 x 1	- 20 to 55
9669	80 - 120	12	1	100	Continuous	2000	12V	- 20 to 55
5672~	5 - 10	12	1	220	Continuous	2000	12V	- 20 to 55
7617~	5 - 15	12	1	220	Continuos	2000	12V	- 20 to 55

\* with on/off switch & 2.5mm DC jack input socket

\*\* 10 channel programable unit with up to 15m on each channel

\*\*\* with photocell

~ for Twin wire

# with on/off switch, 2.5mm DC jack input socket & photocell

**These pages include just some of the inverters we stock.**

**Please ask if you cannot see the unit(s) you require**

Olmecc Advanced Materials Ltd/Surelight

[www.surelight.com](http://www.surelight.com); [info@surelight.com](mailto:info@surelight.com)

[www.olmec.co.uk](http://www.olmec.co.uk); [info@olmec.co.uk](mailto:info@olmec.co.uk)

12 Terminus Rd, Millhouses, Sheffield, S7 2LH. United Kingdom

Tel: +44 (0) 114 236 1606 - Fax: +44 (0) 114 262 1202

GB Reg No. 247 6257 - VAT No. 570 6797 06