

# KD-5 Inverter

Product Code: INV-KD-5



## Key Features

- Designed to drive up to 8m (26.2ft) of Surelight EL Wire
- Operates in 2 modes; continuous & blinking with variable mode
- Portable with mounting clip
- Battery operated by four AAA 1.5V DC
- Low power consumption
- Low audible noise
- LED power indicator

## Product Description

The Surelight KD-5 is a small portable modular inverter designed to drive up to 8m (26.2ft) of Surelight Super Bright EL Wire.

Change from continuous operation to flashing can be achieved using the mode selection switch on the side of the inverter.

The Surelight KD-5 is perfect for EL Wire required for DIY, home decoration, car decoration, signage, event centrepieces, garment and clothing design.

## Specification

### Electronic Specification

Input Voltage	Battery Type	Input Current Range	Output Frequency	Output Voltage Range
6V DC	4x AAA 1.5V DC	65 - 120mA	1.7 - 2KHz	82 - 120 Vrms

### Mechanical Specifications

Dimensions (LxWxH)	Relative Humidity	Weight	Operating Temperature	Storage Temperature
63 x 56 x 27 (mm)	70% RH	90g (with batteries)	-20 - +50 °C	-20 - +60 °C

## Mechanical Dimensions (Unit mm)

